

connecting the future



IFP 522 Power Supply/Inserter +12Vdc - for UFO150 - Blister

Article number: 339531

Product description:

- 12 VDC / 85mA output on RF input for UFO 150
- Automatic switch from 12 VDC to 220 VAC input upon availability
- 1 x RF F-connector input from UFO 150 (12 VDC / 85 mA)
- 2 x RF F-connector outputs for 2 x TV sets.
- Signal insertion loss: 4dB.
- Quick and easy installation
- Install instruction already available on UFO 150 box and manual
- Single packed in compact color retail cardboard box.

Specifications

| | |
|-------------------|---------------|
| ORDER INFORMATION | |
| EAN Number | 5702663395312 |
| CHARACTERISTICS | |
| Type | Power supply |
| FREQUENCY | |
| Frequency range | 47-862 MHz |
| LOSS | |
| Through loss | 4 dB |

| | |
|----------------------------|---|
| ELECTRICAL | |
| Impedance | 75 Ω |
| OPERATIONAL | |
| AC Supply voltage | 230 VAC |
| Power Consumption (typ.) | 3 W |
| PSU output DC voltage | 12 VDC |
| PSU output max. DC current | 85 mA |
| CONNECTORS | |
| Connector Type | F-female |
| Number of inputs | 2 |
| Number of outputs | 2 |
| MECHANICAL | |
| Colour | White |
| Packing QTY | 1 |
| Packaging Height | 0,270 m |
| Packaging Width | 0,160 m |
| Packaging Depth | 0,055 m |
| Packaging Volume | 0,002 m ³ |
| Net Weight | 0,312 kg |
| Tara Weight | 0,055 kg |
| Total Weight | 0,367 kg |
| Remarks | f-connector/DC jack and red/black cable for battery |